Technical Specifications

| Model t602k | PE446AA |
|-------------------------------|---|
| Processor & Speed | 2.53 GHz/533 Intel® Celeron® (P) 325 Processor – PGA478 |
| Chipset . | Intel® 848P |
| Motherboard | Oxford-UL6E (4PSD-LA) |
| RAM | 256/3200 MB 400 DDR SDRAM (runs@333MHz) |
| Maximum | 2 GB (2x1024MB DDR SDRAM) |
| Sockets | Two 184-pin DDR DIMMs |
| Size | 128, 256, 512 AND 1024 MB DDR DIMMs |
| Free DIMM Sockets | One |
| Pairs Required | No |
| Type Supported | JEDEC unbuffered DDR SDRAM DIMM specification |
| Cache | 16KB Data Cache + Trace Cache L1, 256 KB L2 Integrated on Processor module |
| Hard Drive | 120 GB (7200 RPM) |
| Optical Drive | CD-RW/DVD-ROM Drive 48x32x16x48 |
| | 48X- Write /32X - Re-write /16x- DVD Read |
| | 48X - CD-ROM Read |
| Average Random Access | DVD =115ms / CD-ROM =95ms |
| Transfer Rate | DVD = 21.6/sec. / CD-ROM = 7.2MB/sec. |
| Diskette Drive | None |
| 9 in 1 Card Reader | Compact Flash I/II, Memory Stick/PRO, MMC/SD, Smart |
| | Media, xD, Microdrive |
| Video Graphics | AGP 8X Graphics Card |
| Controller | nVidia FX5100-64 |
| Video Memory | 64 MB DDR, not upgradeable |
| Video Connectors | Composite & S-Video - NTSC |
| Network Card | 10/100 BaseT, Integrated |
| 1394 Card | IEEE-1394, Integrated |
| Sound | AC'97, 6 Channel, Integrated on MB |
| Controller | Realtek ALC650 |
| Chassis | Jaguar, 250HV PSU |
| USB Interface Specification | USB 2.0 |
| External I/O Rear Connectors | 4= USB, 1=1394, Serial, Parallel, Line-In, Line-Out; Microphone |
| External I/O Front Connectors | 2=USB;1= 1394, Line In, Microphone, Headphone, 9 in 1 Card Reader w/USB |
| Expansion Slots (Total) | 3= PCI, 1= AGP |
| Expansion Slots (FREE) | 3= PCI |
| Drive Bays (Total) | Two 5.25" external, One 3.5" external, Two 3.5" internal |
| Drive Bays (FREE) | One 5.25" external, One 3.5" external, One 3.5" internal |
| Keyboard/Mouse | One-touch Enhanced Keyboard, PS/2 Optical scrolling mouse |

Copyright Hewlett-Packard Co. 1994-2004
This information is subject to change without notice and is provided "as is" with no warranty.
Hewlett-Packard shall not be liable for any direct, indirect, special, incidental or consequential damages in connection with the use of this material.